19-Dec-2008

## SONY

## like.no.other

# This document was created on

## HT-DDWG800

http://www.sony.co.uk

Cutting edge A/V technologies bring your favourite movies to thrilling HD life. Digital Cinema Sound, x.v. Colour and 24p True Cinema Technology enable you to create an authentic cinema experience at home.



#### **Features**

Please be aware that the features/specifications can differ from country to country.

- Stylish black receiver with premium speakers in a wooden style modern finish
- Pumps out a total of 865W from 5 speakers and a 20cm subwoofer (active) for rich bass
- x.v. Colour and 24p True Cinema technology adjusts picture settings to makes movies look as authentic as the original
- Multi Channel Linear PCM for true High Definition sound
- Put yourself in the middle of the action with Dolby Digital Prologic II / DTS Decoding
- Digital Cinema Sound for a true "at the movies" experience
- 3 HDMI™ inputs (1 out) for a High Definition 1080p experience
- A/V Sync for perfect sound and image synchronisation with flat panel TVs
- DCAC one-push automatic sound set-up for flexible speaker placement and optimum sound quality
- Sony DIGITAL MEDIA PORT connect to and release digital music stored on your WALKMAN® or other mp3 players, mobile phones, Bluetooth® and Wi-Fi devices. (additional accessory required)
- 3x component video inputs
- Front Portable Audio in enables you to connect and access music from WALKMAN®, iPod® and more
- Portable Audio Enhancer function boosts quality of compressed music such as mp3's
- FM / AM radio tuner with RDS and 60 station presets (30 FM + 30 AM)

#### **Useful Links**

Product support
http://www.sony.co.uk

# Technical specifications

#### **Amplifier**

60hms 1kHz (per channel) 135 W/ch 60hms 1kHz (L+R) 90 W + 90 W (60hms 1kHz) THD 1%

Power Output (Total) 135 W x5 + 190 W = 865 W

Number of amp. channels5.1chBi-AMPNOTypeAnalog

4 Ohm / 8 Ohm Switching NO (6 Ohm only)

Circuit Device Discrete
DSP Sharc
OP processing NO
Analog Down Mix NO

Equalizer (F / C / Sur / Sur B) Bass, Mid, Treble B,T / NO / NO / NO

Subwoofer X'Over Fix 150 Hz

Analog Direct NO

Pureness Control NO

Sound Field Link (w Lock) YES (NO)

Sound Field Program (Movie) 3 Sound Field Program (Music) 6 Sound Field Program (A.F.D) 5 Sound Field Program (2ch) Sound Field Program (Headphone) 2 Front Surround Mode (S-Force) NO Portable Audio Enhancer YES Cinema Studio EX. A/B/C mode YES Digital Concert Hall NO X-Round NO Speaker Selector A Only

Speaker Terminal A: Front (Screw) / Others

(Push)

Headphone Out YES (Silver)

### I/Os

USB NO
DIGITAL MEDIA PORT (Level 1) 1 (NO OSD)
IX (Wi-Fi) Optional
Bluetooth® Optional

Connect Optional iPod® Optional Front Input AV

Audio In / Out (excl. tuner)	2/1
A / V In / Out (S-Video I / O): Including Front AV	4 / 1 (NO / NO)
Monitor Out (S-Video Out)	1 (NO)
Component Video In / Out (Pass through)	3 / 1
Phono (MM)	NO
Multi-ch In	NO

## Digital In/Out

HDMI™	3 / 1
i.Link	NO
Opt. : including Front A/V	2/0
Coax.	1 / 0
Digital Input Assign	YES
Pre Out	SW x1

## **Decoding Format**

NO / NO / NO
YES / YES / NO
YES / YES
NO
NO
NO
NO
YES
YES
NO
YES
YES

### Tuner

XM Radio	NO
Neural Audio	NO
Sirius	NO
Preset Channel (XM / FM / AM)	0 / 30 / 30
Station Name	YES
Auto Tuning	YES
Direct Tuning	YES

## Video Features

HDMI™ Repeater	YES
Upscaling (Component / HDMI™)	NO / NO
Video Up Converter (S / Component / HDMI™)	NO / NO / NO
Video Down Converter (Digital / Analog)	NO / NO
A / V SYNC (Variable / Fixed)	YES (Fixed)
Time (msec)	60

Sampling Frequency (96 kHz / 48 kHz)	48 kHz	
Assignable HDMI™ Video IN	NO	
Assignable Component Video IN	NO	

#### DCAC (Digital Cinema Auto Calibration)

 DCAC (DSP / UCOM)
 UCOM

 Band
 NO

 Mic (STEREO / MONO)
 MONO

#### General

Panel Mold (Flat panel) Color Black (Hairline) Remote Commander RM-AAU023 Display 8 Seg. FL Multi Channel Decoding Blue LED NO Sleep Timer YES GUI / OSD NO Pin Jack Nickel Detouchable AC NO AC Outlet (Switched) NO Power Requirements 230V 50 / 60 Hz 200 W Power Consumption Stand by 0.3 Watt

## Speaker cone (Subwoofer)

FTC 28-200Hz THD 1% NO Output Power (1% THD) NO Output Power (10% THD) NO Output Power (RMS) NO Unit size 190 mm Center & Surround speaker package 200 mm Speaker System Bass Reflex Magnetically Shilelded YES Auto Power on / off NO Number Subwoofer 1

#### Speaker cone (front speaker)

Unit size for L,R 80 mm

Speaker System Bass Reflex

Magnetically ShileIded YES

## Speaker cone (surround speaker)

Unit size for Rear 80 mm
Speaker System Bass Reflex

Magnetically Shilelded	NO
Speaker cone (center speaker)	
Unit size for Center	80 mm
Speaker System	Bass Reflex
Magnetically Shilelded	YES
Speaker Connection	
Satellite spks	Push terminal
Subwoofer	RCA Jack
Additional supplied item	
Coaxial cable	NO
Optical cable	NO
Monaural cord (for SW)	YES x1
Speaker cable	3m x3, 8m x 2
HDMI™ Cable	
Supply speaker socket	NO
Wireless radiator / receiver (supplied)	NO
DVD player (supplied)	NO
Easy set up guide (supplied)	YES
Color label for carton box	NO
Speaker Unit Weight & Dimension	
Front Surround Sound Speaker Left	SS-MSP890
Front SS L / Size (WxHxD) mm	130 x 215 x 136 (with foo
Front SS L / Weight (kg)	1.4
Front Surround Sound Speaker Right	SS-MSP890
Front SS R / Size (WxHxD) mm	130 x 215 x 136 (with foo
Front SS R / Weight (kg)	1.4
Center Surround Sound Speaker	SS-CNP890
Center Speaker / Size (WxHxL) mm	245 x 110 x 136 (with foo
Center Speaker / Weight (kg)	1.3
Rear Surround Sound Speaker Left	SS-SRP890
Rear SS L / Size (WxHxD) mm	115 x 170 x 141 (with foo
Rear SS L / Weight (kg)	1.0
Rear Surround Sound Speaker Right	SS-SRP890
Rear SS R / Size (WxHxD) mm	115 x 170 x 141 (with foo
Rear SS R / Weight (kg)	1.0
Subwoofer	SA-WP890
Subwoofer Size (WxHxD) mm	270 x 335 x 380 (with foo
.,	·
Subwoofer Weight (kg)	8.3

Receiver Size (WxHxD) mm	430 x157.5 x 318	
Receiver Weight (kg)	7.8	
Supplied Accessories		
Optimizer Microphone for DCAC used	x1	
Sony Unified Remote	x1	
Rear Speaker Cable: Long	x2	
Monaural audio cord	x1	
FM wire & AM loop Antenna	x1	
Size AA batteries	x2	
Optional Accessories		
DIGITAL MEDIA PORT for iPod® Base	x1	
Speaker Stand: WS-FV11 or WS-FV10D	x1	
DIGITAL MEDIA PORT Base for WALKMAN®	x1	
DIGITAL MEDIA PORT Wi-Fi for PC	x1	
DIGITAL MEDIA PORT Bluetooth® Receiver	x1	

© 2002 - 2008 Sony- Terms and Conditions | Privacy statement